arXiv:1304.6609v1 [math.HO] 23 Apr 2013

ENUMERATION OF VUZA CANONS

FRANCK JEDRZEJEWSKI

ABSTRACT. A Vuza canon is a non periodic factorization of the finite abelian group $\mathbb{Z}_N$. The aim of this paper is to present some new results for generating Vuza canons, and to give new enumerations for some values of N.

Mathematics Subject Classification: 00A65, 97M80.

1. RHYTHMIC CANONS

A rhythmic canon of $Z_N = \{0, 1, 2, ..., N-1\}$ is a factorisation of the finite abelian group Z_N in two subsets S and R such that the sum $S + R$ is direct and equals to Z_N. The set S is called the *inner voice*, and the set of offsets R is the *outer voice*. It is worthy of note that the set S can be seen as a tile of the line Z_N and we said that S tiles Z_N with R or that R tiles with S, since if (S, R) is a rhythmic canon, also is (R, S).

A set A of Z_N is normalized if $\{0\}$ is an element of A. A normalized factorisation of Z_N is a factorisation in two normalized subsets. A set A is *periodic* if there exists a period t, $0 < t < N$ such that $A = A + t$. Around 1948, Hajòs thought that in a factorisation of Z_N in two factors, one of the factors had to be periodic. In fact, this conjecture is false, and counterexamples are precisely Vuza canons. They were introduced by D.T. Vuza under the name of "Regular Complementary Canons of Maximal Category" in his seminal paper [14] and are now known as "Vuza Canons".

Definition 1. *Let Z_N be the finite abelian group $\{0, 1, 2, ..., N-1\}$, S and T be two subsets of Z_N. A Vuza Canon (S, R) is a rhythmic canon*

$$Z_N = S + R$$

where neither S, nor R is periodic.

In 1962, A.D. Sands [12, 13] gave the classification of all finite abelian groups which are called "Hajós groups" or "good groups" [7]. The first Vuza canon appears for $N = 72$, and the next one occurs at $N = 108$, 120, 144, 168, etc. More precisely, we have the following result classifying good (and bad) groups.

Theorem 2. *The following propositions are equivalent:*
(i) Vuza canons only exist for periods N which are not of the form

$$N = p^\alpha, \quad p^\alpha q, \quad p^2q^2, \quad p^2qr, \quad pqrs$$

where p, q, r, s are different primes.
(ii) Vuza canons only exist for periods N of the form

$$N = n_1n_2n_3p_1p_2$$

where p_1, p_2 are different primes, $p_in_i \geq 2$, for $i = 1, 2$ and $\gcd(n_1p_1, n_2p_2) = 1$.

As shown by E. Amiot [2], rhythmic canons are stable by duality, affine transformation, concatenation, zooming and stuttering. Duality is the exchange between inner and outer voices. If (S, R) is a Vuza canon, then (R, S) is also a Vuza canon as the addition is commutative. The stability by affine transformation $x \to ax + b$, where a is coprime with N is not obvious (see [1]). However, the stability by concatenation states as follows.

Theorem 3. *Let k be a positive integer.*
(i) If (S, R) is a Vuza canon of Z_N, then $(S + NZ_k, R)$ is a Vuza canon of Z_{Nk}.
(ii) Conversely, if (S, R) is a Vuza canon of Z_{Nk} and if S is a subset of Z_N, then $(S, R \cap Z_N)$ is a Vuza canon of Z_N.

Proof. (i) Since (S, R) is a Vuza canon of Z_N, we have $S + NZ_k + R = Z_N + NZ_k = Z_{Nk}$. Moreover, the set $S + NZ_k$ remains non-periodic, since S is.

(ii) The equations

$$\begin{aligned} Z_N &= Z_{kN} \cap Z_N \\ &= (S + R) \cap Z_N \\ &= S + (R \cap Z_N) \end{aligned}$$

show that Z_N is the sum of S and $R \cap Z_N$, as S is a subset of Z_N. This sum is direct since the sum $S + R$ is. Moreover, suppose that $R \cap Z_N$ is periodic. Then, there exists a period t, $0 < t < N$ such that

$$\begin{aligned} R \cap Z_N &= t + (R \cap Z_N) \\ &= (t + R) \cap (t + Z_N) \\ &= (t + R) \cap Z_N \end{aligned}$$

which implies that t is a period of R and leads to a contradiction, since R is non-periodic. ☐

2. Constructing Vuza Canons

In 2004 at the Mamux Seminar, I gave a solution for constructing large Vuza canons, depending only on the parameters n_1, n_2, n_3, p_1 and p_2. Let us rephrase this result in the following manner:

Theorem 4. *Let p_1, p_2 be different prime numbers, and n_1, n_2, n_3 be positive integers such that the product $n_1 p_1$ is coprime with $n_2 p_2$, then the pair (S, R) defined by*

$$\begin{aligned} S &= A + B \\ R &= (U + V' + K_1) \cup (U' + V + K_2) \end{aligned}$$

is a Vuza canon, with:

$$\begin{array}{ll} A = n_1 p_1 n_3 Z_{n_2} & B = n_2 p_2 n_3 Z_{n_1} \\ U = n_1 n_2 n_3 p_1 Z_{p_2} & V = n_1 n_2 n_3 p_2 Z_{p_1} \\ U' = n_2 n_3 Z_{p_2} & V' = n_1 n_3 Z_{p_1} \\ K_1 = \{0\} & K_2 = \{1, 2, ..., n_3 - 1\} \end{array}$$

The proof of this theorem is straightforward using the following main lemma:

Lemma 5. *Let a, b, c be positive integers such that a is coprime with c. We have*

$$\begin{array}{ll} (i) & Z_a + aZ_b = Z_{ab} \\ (ii) & cZ_a + aZ_{bc} = Z_{abc} \end{array}$$

The previous theorem has at least two generalizations. The first one consists in choosing the sets K_1 and K_2 amongst a complete set K of coset representatives for Z_N modulo a proper non-zero subgroup H.

Theorem 6. *Let H be the subgroup $H = n_3 Z_{n_1 p_1 n_2 p_2}$ of Z_N with $N = n_1 n_2 n_3 p_1 p_2$, and K be a complete set of cosets representatives for Z_N modulo H such that $K = K_1 \cup K_2$. Let p_1, p_2 be different prime numbers, and n_1, n_2, n_3 be positive integers such that $n_1 p_1$ is coprime with $n_2 p_2$, then the pair (S, R) defined by*

$$\begin{aligned} S &= A + B \\ R &= (U + V' + K_1) \cup (U' + V + K_2) \end{aligned}$$

is a Vuza canon, with:

$$\begin{array}{ll} A = n_1 p_1 n_3 Z_{n_2} & B = n_2 p_2 n_3 Z_{n_1} \\ U = n_1 n_2 n_3 p_1 Z_{p_2} & V = n_1 n_2 n_3 p_2 Z_{p_1} \\ U' = \alpha n_2 n_3 Z_{p_2} & V' = \beta n_1 n_3 Z_{p_1} \end{array}$$

and $\alpha = 1, n_1$ or p_1, and $\beta = 1, n_2$ or p_2.

Proof. Since $\beta = 1$ or β is coprime with p_1, we have by the main lemma

$$\begin{aligned} A + U + V' &= n_1 p_1 n_3 Z_{n_2} + n_1 n_2 n_3 p_1 Z_{p_2} + \beta n_1 n_3 Z_{p_1} \\ &= n_1 p_1 n_3 (Z_{n_2} + n_2 Z_{p_2}) + \beta n_1 n_3 Z_{p_1} \\ &= n_1 p_1 n_3 Z_{n_2 p_2} + \beta n_1 n_3 Z_{p_1} \\ &= n_1 n_3 (\beta Z_{p_1} + p_1 Z_{n_2 p_2}) \\ &= n_1 n_3 Z_{n_2 p_1 p_2} \end{aligned}$$

In the same way,

$$\begin{aligned} A + U + V &= n_1 p_1 n_3 Z_{n_2} + n_1 n_2 n_3 p_1 Z_{p_2} + n_1 n_2 n_3 p_2 Z_{p_1} \\ &= n_1 p_1 n_3 (Z_{n_2} + n_2 Z_{p_2}) + n_1 n_2 n_3 p_2 Z_{p_1} \\ &= n_1 p_1 n_3 Z_{n_2 p_2} + n_1 n_2 n_3 p_2 Z_{p_1} \\ &= n_1 n_3 (p_1 Z_{n_2 p_2} + n_2 p_2 Z_{p_1}) \\ &= n_1 n_3 Z_{n_2 p_1 p_2} \end{aligned}$$

The same expression can be set for B:

$$\begin{aligned} B + V + U' &= n_2 p_2 n_3 Z_{n_1} + n_1 n_2 n_3 p_2 Z_{p_1} + \alpha n_2 n_3 Z_{p_2} \\ &= n_2 p_2 n_3 (Z_{n_1} + n_1 Z_{p_1}) + \alpha n_2 n_3 Z_{p_2} \\ &= n_2 p_2 n_3 Z_{n_1 p_1} + \alpha n_2 n_3 Z_{p_2} \\ &= n_2 n_3 (p_2 Z_{n_1 p_1} + \alpha Z_{p_2}) \\ &= n_2 n_3 Z_{n_1 p_1 p_2} \end{aligned}$$

and

$$\begin{aligned} B + V + U &= n_2 p_2 n_3 Z_{n_1} + n_1 n_2 n_3 p_2 Z_{p_1} + n_1 n_2 n_3 p_1 Z_{p_2} \\ &= n_2 p_2 n_3 (Z_{n_1} + n_1 Z_{p_1}) + n_1 n_2 n_3 p_1 Z_{p_2} \\ &= n_2 p_2 n_3 Z_{n_1 p_1} + n_1 n_2 n_3 p_1 Z_{p_2} \\ &= n_2 n_3 (p_2 Z_{n_1 p_1} + n_1 p_1 Z_{p_2}) \\ &= n_2 n_3 Z_{n_1 p_1 p_2} \end{aligned}$$

Using these relations, we get

$$\begin{aligned} S+R &= (A+B)+((U+V'+K_1)\cup(U'+V+K_2)) \\ &= (A+B+U+V'+K_1)\cup(A+B+U'+V+K_2) \\ &= (A+B+U+V+K_1)\cup(A+B+U+V+K_2) \\ &= A+B+U+V+(K_1\cup K_2) \\ &= (A+U)+(B+V)+K \end{aligned}$$

And since

$$X = A+U = n_1n_3Z_{n_2p_2}$$
$$Y = B+V = n_2n_3Z_{n_1p_1}$$

it follows that

$$H = X+Y = n_3Z_{n_1p_1n_2p_2}$$

and so, for any set K such that

$$H+K = Z_N$$

the Vuza canon (S,R) is a direct sum of Z_N. □

The demonstration depends only on the formulas of the lemma. Changing the defintion of H leads to a new theorem.

Theorem 7. *Let H be the subgroup $H = p_1Z_{n_1n_2n_3p_2}$ of Z_N with $N = n_1n_2n_3p_1p_2$, and K be a complete set of cosets representatives for Z_N modulo H such that $K = K_1\cup K_2$. Let p_1, p_2 be different prime numbers, and n_1,n_2,n_3 be positive integers such that n_1p_1 is relatively prime with n_2p_2, and n_1n_3 is relatively prime with n_2p_2*

$$\gcd(n_1n_3,n_2p_2)=1$$

then the pair (S,R) defined by

$$\begin{aligned} S &= A+B \\ R &= (U+V'+K_1)\cup(U'+V+K_2) \end{aligned}$$

is a Vuza canon, with:

$$\begin{array}{ll} A = n_1p_1n_3Z_{n_2} & B = n_2p_2p_1Z_{n_1} \\ U = n_1n_2n_3p_1Z_{p_2} & V = n_1p_1Z_{n_3} \\ U' = n_2p_1Z_{p_2} & V' = n_1p_1n_2p_2Z_{n_3} \end{array}$$

Or to its dual version:

Theorem 8. *Let H be the subgroup $H = p_2Z_{n_1n_2n_3p_1}$ of Z_N with $N = n_1n_2n_3p_1p_2$, and K be a complete set of cosets representatives for Z_N modulo H such that $K = K_1\cup K_2$. Let p_1, p_2 be different prime numbers, and n_1,n_2,n_3 be positive integers such that n_1p_1 is relatively prime with n_2p_2, and n_1p_1 is relatively prime with n_2n_3*

$$\gcd(n_1p_1,n_2n_3)=1$$

then the pair (S,R) defined by

$$\begin{aligned} S &= A+B \\ R &= (U+V'+K_1)\cup(U'+V+K_2) \end{aligned}$$

is a Vuza canon, with:

$$\begin{array}{ll} A = n_1p_1p_2Z_{n_2} & B = n_2n_3p_2Z_{n_1} \\ U = n_1n_2p_1p_2Z_{n_3} & V = n_1n_2n_3p_2Z_{p_1} \\ U' = n_2p_2Z_{n_3} & V' = n_1p_2Z_{p_1} \end{array}$$

The second generalization of the first theorem consists in constructing the sets U' and V' by adding a set of elements of respectively B and A.

Theorem 9. *Let H be a proper non-zero subgroup of Z_N, such that H is the direct sum of two subgroups X and Y of composite orders relatively prime* $\gcd(|X|, |Y|) = 1$. *Let U be a non-zero proper subgroup of X and A a non-periodic subset such that $X = A+U$. Let V be a non-zero proper subgroup of Y, B a non-periodic subset such that $Y = B + V$, and K be a complete set of cosets representatives for Z_N modulo H such that $K = K_1 \cup K_2$. Construct the set U' by replacing non-zero elements $u_j \in U$ by their sum with some non-zero elements of B (non necessary different)*

$$U' = (U \backslash \{u_1, ..., u_n\}) \cup \{u_1 + b_1, ..., u_n + b_n\}$$

and the set V' by replacing some non-zero elements $v_i \in V$ by their sum with some non-zero elements of A

$$V' = (V \backslash \{v_1, ..., v_m\}) \cup \{v_1 + a_1, ..., v_m + a_m\}$$

Then the pair

$$\begin{aligned} S &= A + B \\ R &= (U + V' + K_1) \cup (U' + V + K_2) \end{aligned}$$

is a Vuza canon of Z_N.

Proof. Since $b_j \in B$,

$$\begin{aligned} U' + B &= (U \backslash \{u_1, ..., u_n\}) \cup \{u_1 + b_1, ..., u_n + b_n\} + B \\ &= (U + B \backslash \{u_1 + B, ..., u_n + B\}) \cup \{u_1 + b_1 + B, ..., u_n + b_n + B\} \\ &= (U + B \backslash \{u_1 + B, ..., u_n + B\}) \cup \{u_1 + B, ..., u_n + B\} \\ &= U + B \end{aligned}$$

and since $a_i \in A$,

$$\begin{aligned} V' + A &= (V \backslash \{v_1, ..., v_m\}) \cup \{v_1 + a_1, ..., v_m + a_m\} + A \\ &= (V + A \backslash \{v_1 + A, ..., v_m + A\}) \cup \{v_1 + a_1 + A, ..., v_m + a_m + A\} \\ &= (V + A \backslash \{v_1 + A, ..., v_m + A\}) \cup \{v_1 + A, ..., v_m + A\} \\ &= V + A \end{aligned}$$

The sum $S + R$ is then equals to

$$\begin{aligned} S + R &= (A + B) + ((U + V' + K_1) \cup (U' + V + K_2)) \\ &= (A + B + U + V' + K_1) \cup (A + B + U' + V + K_2) \\ &= (A + B + U + V + K_1) \cup (A + B + U + V + K_2) \\ &= A + B + U + V + (K_1 \cup K_2) \\ &= A + B + U + V + K \\ &= X + Y + K \\ &= H + K = Z_N \end{aligned}$$

The two subsets A and B are supposed to be non-periodic. Since the sum $X + Y$ is direct, the sum $\langle A \rangle + B$ is direct and S is non-periodic. The non-periodicity of R is more difficult to prove. Suppose that t is a period of R. (1) If t belongs to H, then t can be written uniquely $t = x + y$ since the sum $H = X + Y$ is direct. But if t is a period of R, t is a period of $U' + V$ and a period of $U + V'$, and then x is a period of U' and y is a period of V. Since U' is a non-periodic set, it follows that $x = 0$ and $y = t$ belongs to V. In the same way, since t is a period of $U + V'$ and V' is a non-periodic set, il follows that t belongs to U. But the intersection of

U and V is $\{0\}$, this implies that $t = 0$, and then that t can not be a period of R. (2) Now, if t does not belong to H, t can be decomposed as a sum $t = h + k$, with $h \in H$ and $k \in K$, since the sum $H + K = Z_N$ is direct. From

$$U + V' + t = U' + V + k$$

it follows that

$$U + V' + h = U' + V$$

But $U + V'$ and $U' + V$ are periodic and have no period in common, it follows that the last equation is impossible and so R is non-periodic. □

Remarque 10. *Let $\mathcal{R}$ be the set of all possible sets $\{U+V', U'+V\}$, for all U, U', V and V'. Decomposing K as the union*

$$K = \bigcup_{j=1}^{n_3} K_j$$

and choosing n_3 different R_j in $\mathcal{R}$, it is easy to verify that the pair (S,R) with S as above and

$$R = \bigcup_{j=1}^{n_3} (R_j + K_j)$$

is a Vuza canon.

Knowing a Vuza Canon (S, R), new canons can be generated by applying the above construction to the S part. More precisely,

Theorem 11. *Let A, B, U, V, U', V', K_1 and K_2 defined as above and such that the pair (S,R) with*

$$\begin{aligned} S &= A + B \\ R &= (U + V' + K_1) \cup (U' + V + K_2) \end{aligned}$$

is a Vuza Canon. Construct the set A' by replacing non-zero elements $a_j \in A$ by their sum with some non-zero elements of U

$$A' = (A \backslash \{a_1, ..., a_n\}) \cup \{u_1 + a_1, ..., u_n + a_n\}$$

and the set B' by replacing some non-zero elements $b_i \in B$ by their sum with some non-zero elements of V

$$B' = (B \backslash \{b_1, ..., b_m\}) \cup \{v_1 + b_1, ..., v_m + b_m\}$$

Then the pair (S', R) with $S' = A' + B'$ is a Vuza canon of Z_N.

Proof. The proof is straightforward since $A' + U = A + U$, and $B' + V = B + V$. Notice that elements u_j (resp. v_j) are not necessary different. □

Theorem 12. *Let A, B, U, V, U', V', K_1 and K_2 defined as above and such that the pair (S,R) with*

$$\begin{aligned} S &= A + B \\ R &= (U + V' + K_1) \cup (U' + V + K_2) \end{aligned}$$

is a Vuza Canon. Suppose that L and M are proper subgroups of $K = Z_{n_3}$ such that $Z_{n_3} = L + M$ is a direct sum. The pair (S', R') with

$$\begin{aligned} S' &= A + B + L \\ R' &= (U + V' + M_1) \cup (U' + V + M_2) \end{aligned}$$

is a Vuza canon.

Proof.

$$\begin{aligned} S' + R' &= (A + B + L + U + V' + M_1) \cup (A + B + L + U' + V + M_2) \\ &= A + B + L + U + V + (M_1 \cup M_2) \\ &= H + K = Z_N \end{aligned}$$

□

Theorem 13. *Let k be a positive integer. If the pair (S, R) is a Vuza canon of Z_N, then (S', R') with*

$$\begin{aligned} S' &= kS + Z_k \\ R' &= kR \end{aligned}$$

is a Vuza canon of Z_{Nk}.

Proof. By the main lemma, we have

$$S' + R' = k(S + R) + Z_k = Z_k + kZ_N = Z_{Nk}$$

□

3. Computing Vuza Canons

From the musical point of view, canons could be translated without changing their identity. If (S, R) is a canon of Z_N, any translate of S tiles with the same R. That is why canons are identified by their *prime form*, that is the smallest circular permutation of the set of their consecutive intervals. If S is a set of Z_N, $S = (s_1, s_2, ..., s_n)$, the prime form of S is the smallest circular permutation of

$$\Delta S = (s_2 - s_1, s_3 - s_2, ..., s_n - s_{n-1}, s_1 - s_n)$$

The results of the previous section provide us a way for computing Vuza canons.

(1) Determine a proper subgroup H of Z_N such that H is a direct sum of two subgroups X and Y of relatively prime composite orders. For a given $N = n_1 n_2 n_3 p_1 p_2$, where p_1, p_2 are different primes, $p_i n_i \geq 2$, for $i = 1, 2$ and $\gcd(n_1 p_1, n_2 p_2) = 1$, there always exists at least one such subgroup

$$H = n_3 Z_{n_1 p_1 n_2 p_2}, \qquad X = n_1 n_3 Z_{n_2 p_2}, \qquad Y = n_2 n_3 Z_{n_1 p_1}$$

but it could exist more than one. For example, for $N = 144$, we have two solutions: $H = 2Z_{72} = 16Z_9 + 18Z_8$ and $H = 4Z_{36} = 36Z_4 + 16Z_9$. Next, decompose H as a direct sum of X and Y, and each set as $X = A + U$ and $Y = B + V$.

(2) Compute the list of all possible sets A by theorem 11, the list of all possible sets B and deduce all prime form of $S = A + B$.

(3) Compute the set of coset representatives such that $Z_N = H + K$. If K can be decompose as a sum of two proper subgroups $K = L + M$ as in theorem 12, compute the new orbit of Vuza canons $S = A + B + L$, and memorize all prime forms.

(4) For a prime form S of each orbit, obtained as above or by switching n_1 and n_3, compute the prime forms of R, using the results of the previous section and remark 10.

The computation of the number of Vuza canons up to circular permutations leads to the following tables. The length of S is $|S| = n_1 n_2$ and the length of R is $|R| = n_3 p_1 p_2$. The results depicted in the first table are well-known.

N	n_1	p_1	n_2	p_2	n_3	$\|S\|$	$\|R\|$	$\#S$	$\#R$
72	2	2	3	3	2	6	12	3	6
108	2	2	3	3	3	6	18	3	252
120	2	2	3	5	2	6	20	8	18
–	2	2	5	3	2	10	12	16	20
144	2	2	3	3	4	6	24	3	8640
–	2	2	3	3	4	6	24	6	36
–	4	2	3	3	2	12	12	6	60
–	4	2	3	3	2	12	12	162	12
–	4	2	3	3	2	12	12	324	6
168	2	2	3	7	2	6	28	16	54
–	2	2	7	3	2	14	12	104	42

The second table shows new results. Due to too long computing times, some orbits are missing.

N	n_1	p_1	n_2	p_2	n_3	$\|S\|$	$\|R\|$	$\#S$	$\#R$
180	2	2	3	3	5	6	30	3	77760
–	2	2	3	5	3	6	30	8	2052
–	2	5	3	3	2	6	30	3	84
–	2	2	5	3	3	10	18	16	1800
–	3	3	5	2	2	15	12	9	105
200	2	2	5	5	2	10	20	125	60
216	2	2	9	3	2	18	12	575	72
–	4	2	3	3	2	12	18	6	13680
240	4	2	5	3	2	20	12	32	200
–	4	2	3	5	2	12	20	4100	16
252	2	2	3	7	3	6	42	16	396
–	2	7	3	3	2	6	42	9	366
264	2	2	3	11	2	6	44	40	558
270	5	2	3	3	3	15	18	9	50400
280	2	2	5	7	2	10	28	425	180
–	2	2	7	5	2	14	20	2232	126
300	2	3	5	5	2	10	30	104	240
–	3	2	5	5	2	15	20	104	480
324	2	2	9	3	3	18	18	729	16848
336	4	2	3	7	2	12	28	32	7020
–	4	2	7	3	2	28	12	208	420
392	2	2	7	7	2	14	28	16807	378
400	4	2	5	5	2	20	20	250	2040
450	3	3	5	5	2	15	30	375	1920

4. CONCLUSION

The aim of this paper was to show how to construct Vuza canons and to compute their numbers for some value of N. We established new theorems helping us to elaborate a faster algorithm. But in many cases, the number of solutions is quite large, and some shortcuts have to be found.

References

[1] Amiot, E. Rhythmic canons and Galois theory, *Colloquium on Mathematical Music Theory*, Grazer Math. Ber., Nr. 347, 1-21, 2005.

[2] Amiot E. "Structures, Algorithms, and Algebraic Tools for Rhythmic Canons" *Perspectives of New Music*, 49 (2) 93-142, 2011.

[3] Andreatta M., Agon, C. and Amiot, E. "Tiling problems in music composition: Theory and Implementation", *International Computer Music Conference*, Göteborg, 156-163, 2002.

[4] Brujin N.G. On the factorization of finite abelian groups, *Indag. Math.* 15, 258–264, 1953.

[5] Coven E. and Meyerowitz A. "Tiling the integers with translates of one finite set.", *J. Algebra*, 212, 161-174, 1999.

[6] Fripertinger H. "Enumeration of nonisomorphic canons", *Tatra Mt. Mathematical Publications*, 23, 47-57, 2001.

[7] Hajós H. Sur la factorization des groupes abéliens. *Casopis Pest Mat. Fys.*, 74, 157–162, 1950.

[8] Jedrzejewski F. *Mathematical Theory of Music*, Ircam/Delatour, 2006.

[9] Jedrzejewski F. Tiling the integers with aperiodic tiles, *Journal of Mathematics and Music* 3 (2) 99-115, 2009.

[10] Kolountzakis M. and Lagarias J. Structure of tilings of the line by a function. *Duke Mathematical Journal*, 82 (3), 653–678, 1996.

[11] Lagarias J. and Wang Y. Tiling the line with translates of one tile. *Inventiones Mathematicae*, 124 (1), 341–365, 1996.

[12] Sands A. D. On the factorisation of finite abelian groups. I. *Acta Mathematica Hungarica*, 8, 65–86, 1957.

[13] Sands A. D. On the factorisation of finite abelian groups. II. *Acta Mathematica Hungarica*, 13, 153–169, 1962.

[14] Vuza, D. T. Supplementary Sets and Regular Complementary Unending Canons, *Perspectives of New Music*, 29 (2) 22-49; 30 (1), 184-207; 30 (2), 102-125; 31(1), 270-305, 1991.